## Installing and Configuring Mac Print Driver

## Set up LPD

Note: Screen shots are from OS X 10.8.

- Under the Apple menu, open System Preferences and click Print & Scan (In Mac OS X 10.6, this is Print & Fax). Result: The Print & Scan window opens. Note: If the padlock in the lower-left corner is closed, click it and enter the Macintosh administrator name and password.

Show All	Pi	ç
		No printers are available. Click Add (+) to set up a printer.
+ -	Default printer:	Last Printer Used \$
+ -	Default printer: Default paper size:	Last Printer Used     \$       US Letter     \$

To add a printer, click the + (plus) sign. Result: The Add Printer setup window opens.



!. To add a printer, click the + (plus) sign. Result: The Add Printer setup window opens.



In the window you will enter 10.1.170.50 for the Address and in the Queue You will enter lower case mac

00	Add Printer	$\bigcirc$
	۹ 🖨	
Default Fax	IP Windows	Search
Protocol	Internet Printing Protocol – IPP	•
Address:	10.1.170.50	
	Valid and complete address.	
Queue:	mac	
	Leave blank for default queue.	
Name:		
Location:	· · · · · · · · · · · · · · · · · · ·	
Print Using:	RICOH Aficio	\$
More Printe	ers	Add
		//

5. Next, click on the drop down menu for "Print Using" and choose "Select Printer Software".

Auto ✓ Gener Gener Select	Select ric PostScript Printer ric PCL Laser Printer t Printer Software	
Other	·	
	Auto Select ✓ Generic PostScript Printer Generic PCL Printer <u>Select Printer Software</u> Other	

When you are prompted for the print driver Select Printer Software and go to the Ricoh printers and select the Ricoh PS C4000 PPD. Once installed you will need to configure the User ID setting as shown below.

Printer: FPSD-CIRIC18	3			
Presets: Standard		÷ 5		
? PDF  Preview	Cancel	Print		
lick where it says Copies & Page	s and select Job Lo	g		
	Print			
<b>B</b> 1 1 ( <b>FB</b>				•
Printer: FP	SD-CIRIC183			
Presets: Sta	andard	\$		
✓ Co	pies & Pages			
Mi	crosoft Word	2		
La	vout	Copress: 1	🕄 🗹 Collated	
Co	lor Matching			
Pa	per Handling			
Pa	per Feed	ent Page		
Co	ver Page	tion		
Sc	heduler	1: 1		
lot	o Log	5: 1		

Print
Printer: FPSD-CIRIC183
Presets: Standard
Job Log
User ID: Josh
(Up to 8 alphanumeric characters)
Job Type 🗸 Normal Print
File Name Locked Print
Hold Print
Password Stored Print
Store and Print Document Server
User Code:
(Up to 8 digits)
(?) (PDF v) (Preview) (Cancel (Print)

In the image above you will enter your LDAP ID in the User ID box. You can leave the Job Type on Normal Print. The LDAP ID is usually your first initial and first 5 or 6 characters of your last name. Once this has been done you will need to save this configuration as you Default Preset.

Print
Printer: FPSD-CIRIC183
Presets ✓ Standard Last Used Settings
Save
Fit to Paper: Pr Delete
Resolution: 600 dpi
Print Mode: Off
Image Smoothing: Off
Color Mode: Black and White
Gradation: Standard
?     PDF ▼     Preview     Cancel     Print

You are now ready to Print using the Mac Print Driver.