

HBD Electronics


- Preamp/cable driver on the detector.
 - Specification
 - Schematics
 - Test result
- Rest of the electronics chain located in the rack.
 - Cable
 - Block diagram
 - Individual components
- HBD LL1 trigger
- Outlook

Charge Preamp with On-Board Cable Driver **(IO1195-1-REVA)**

Features:

- 1) **+/- 5V power supply.**
- 2) **165 mW power dissipation.**
- 3) **Bipolar operation ($Q_{input} = +/-$)**
- 4) **Differential outputs for driving 100 ohm twisted pair cable.**
- 5) **Large output voltage swing -- +/- 1.5V (cable terminated at both ends)**
(+/- 3V at driver output)
- 6) **Low noise: $Q_{noise} = 345e$ ($C_{external} = 5pF$, $shaping = .25us$)**
($C_f = 1pF$, $R_f = 1meg$)
- 7) **Size = 1.04" x 0.775" 10pins**
- 8) **Preamp output (internal) will operate +/- 2.5V to handle large pile-up.**


IO1195-1- REVA




Test with GEM Detector

PA Pulse Trace on Scope →

- Input capacitance ~ 0.0 pF??
- $20 \text{ pe} \times 5\text{E}3$ (gain) $\sim 100,000$ electron input into pre-amp
- Baseline Noise $\sim 1100\text{e}^-$'s after background is subtracted off.



ADC Data: Fe 55 Pulse Height Spectrum in pure CF4 (IO1195 PreAmp)



MARCH 9, 2005

→ PA Pulse Height Spectrum

B.Azmoun

R Review





Use 2MM Hard Metric cable to move signals between preamp/FEM

2mm HM connector has 5 pins per row and 2mm spacing between pins and rows


There are two types of cable configuration:

*100 ohms parallel shielded cable

50 ohms coaxial cable



Signal arrangement




Our choice is

This gives us signal density 2mm x 10mm for every 2 signals.
Same type of cables will be used for L1 trigger data.


HBD FEM

- 48 channels per FEM
 - 12(11) bits 60MHz sampling per channel.
 - 3 bits LL1 data output per channel
 - 7 individual threshold levels per channel
 - Optical output to DCM, 6xbeam crossing rate(~60MHz).
 - Use commercial 8b/10b chip (TI) plus optical transceiver
 - 6UX220mm card size
- Interface module
 - GTM (clock, L1 trigger etc.), Ethernet interface for slow download.
 - Control test pulse.
- 6U x 220 mm card size
- HBD readout will fit into 3 6U crates
- HBD LL1 module potentially could fit into one 6U crate.

FEM Block Diagram




FEM Crate Diagram




The differential receiver

Use Analog Device
 AD8138 receiver
 set up as unity gain



Total voltage
 On the cable

Total voltage
 Seen by ADC



Simulation result
 For 16fc input
 charge

ADC has 1V range
 Max ADC range is
 about ~10 time of 16fc

FPGA

- Receive ADC data, provide L1 delay, Multiple L1 triggered events, format data, generating L1 trigger primitives, transfer L1 trigger data ,manage clocks and test pattern etc.
- 48 channel of serial ADC => 48 *720 Mbits/sec or 34 Gbits/sec need to be received.
- We choice Altera Stratix II 90nm EP2S60 1020 pins to received the ADC data.


Signal Flow



current progress
on the FEM board

Differential receiver

Signal input



Majority of boards is set
We now try to deal with the power issues

- +3.3 for ADC
- +/- 2.5V for receiver
- FPGA needs
 - +3.3V, +2.5V, +1.2V

HBD data to DCM

- 12 samples per channel
 - Cover 2 beam crossing
- Assume the optical will run 6X beam crossing rate.
 - 48 channel will take $\sim 16.6 \text{ ns} * 48 * 12 = 9.6$ microsec.
- We will merge 4 FEMs' data into one optical link in un-multiplexed mode

HBD L1 trigger

- Each FEM output 3 bits per channel, 7 threshold setting.
 - Total bandwidth is $3 \times 48 \text{ channel} \times 9.6 \text{ MHz} \sim 1.4 \text{ GHz}$ ($\sim 1.7 \text{ GHz}$ optical bandwidth)
 - Multiplex FEM L1 data into 3 differential pairs + 1 clock pair cable
 - Use 4mm vertical space.
- The HBD LL1 crate could locate within the HBD FEM rack.
- Each arm of the HBD has 12 panels. Each panel has 96 channels. Each FEM cover 48 channels.
 - Each LL1 covers 24 FEM's data
 - Generic LL1 has 16 optical inputs
- The Stratix II EP2S60 chip can receive 8 FEM inputs. 3 chips could cover 24 FEM's data.
- We should have enough logic to deal with reasonable trigger algorithms.
- HBD LL1 decisions will be send to GL1 and LL1 calculation result will be send to DCM.

Outlook

- The prototype FEM layout will be done soon.
- We need to work on the interface board and dataway.
 - Test can be underway once these boards exist.
- Need to deal with how to receive optical data in the DCM end.
 - Probably with a special daughter card