

ACCELERATION :*

The central difficulty in a $\mu^+\mu^-$ COLLIDER is: **MUON DECAY**. They must be collected, cooled, accelerated and collided within lifetime.


Acceleration system must accommodate fairly large phase space and compress it to match the requirements of the collider

- **Lifetime Constraints**

$$\text{Decay rate } \frac{dN}{ds} = -\frac{1}{L\mu\gamma} \quad L\mu c\tau_\mu \approx 660 \text{ m}$$

$$\text{Assume low losses } \rightarrow eV'_{\text{rf}} \gg 0.16 \frac{\text{MeV}}{\text{m}}$$

*




$\mu^+\mu^-$ COLLIDER


- Scenarios

1. Sequence of linacs (VERY EXPENSIVE)
2. Recirculating linacs with multiple arcs (similar to CEBAF) (RELATIVELY EXPENSIVE)
3. Synchrotrons with fast pulsed magnets with long SC linacs (MORE ECONOMICAL)
4. (250 GeV) 4 T pulsed magnets ($t=1$ msec)
5. (2 TeV) Interlace of fixed 8 T SC dipole magnets with ± 2 T pulsed magnets

†

†


 $\mu^+ \mu^-$ COLLIDER



Cross sections of pulsed current dipoles for a μ rapid-cycling accelerator dipole (4 T)

‡


 $\mu^+ \mu^-$ COLLIDER




Cross sections of pulsed current dipoles for a collider dipole (6 T).


§

§

 $\mu^+ \mu^-$ COLLIDER




Ramp for rapid-cycling pulsed-dipoles for acceleration to 250 GeV ¶




$\mu^+ \mu^-$ COLLIDER

0.25 - 1.3 TeV & 1.3 - 2 TeV Accelerators



A scale drawing of a possible 4 TeV muon
collider machine ||

||


 $\mu^+ \mu^-$ COLLIDER

Parameters for pulsed conductor-dominated
accelerator and storage ring dipoles

Parameter unit	Accelerator <i>Dipole</i>	Storage Ring <i>Dipole</i>
Coil r_{inner} (cm)	2	2
Magnet length (m)	10	10
Field (T)	4	6
Current (kA)	29.5	24.9
Stored energy (kJ)	160	360
Inductance (mH)	0.37	1.2
Coil R (mW)	19	44
Ramp time (μs)	360	
Store Time (μs)		5000
Power supply V (kV)	31.2	1.1
P. into mag. at 2 Hz (kW)	19	452
Power into ring (MW)	2.7	39.4

**

**



$\mu^+ \mu^-$ COLLIDER