

PRM Commands

Command Name	Keyboard Entry	Range
Projected Track Intensity	VI (n)	N = 1 - 4
Range Rings Intensity	RI (n)	N = 1 - 4
Map Intensity	MI (n)	N = 1 - 4
Centerline Deviation Lines Intensity	CI (n)	N = 1 - 4
Data Block Intensity	DI (n)	N = 1 - 4
Text Intensity	TI (n)	N = 1 - 4
Data Block Character Size	CS (n)	N = 1 - 4
Data Block Leader Line		
Auto Offset Toggle On/Off	[F7] O	n/a
Data Block Intensity	DI (n)	N = 1 - 4
Leader Line Angle	[F7] L (n) (slew)	N = 1 - 9 except 5
Leader Line Length	LL (n)	N = 1 - 8
History Trail Control	HT (n)	N = 0 - 16
Move Status Area	[F7] ST (slew)	n/a
Move Coast List	[F7] TC (slew)	n/a
Move System Data Area	[F7] S (slew)	n/a
Move Preview Area	[F7] P (slew)	n/a
Set Barometric Pressure/Time	[F7] S (n)	N = 2700 - 3400 for altimeter
Text Size	TS (n)	N = 1 - 3
Set System Date	DATE_(ddmmmyy)	n/a
Toggle Status Area Display	ST	n/a
Toggle Parallel Line	PL	n/a
Range Ring Control	RR (n)	N = 0 - 15
List Setups	LCS	n/a
Restore Setup	CRES_(name)	10 Names Maximum
Restore Default Setup	CDEF	n/a
Runway Configuration	(RW#) A	n/a

Command Name	Keyboard Entry	Range
--------------	----------------	-------

Silence Alarm System	SSYS	n/a
Switch Channel	CH (n)	N = 1 - 2
BRS Start	GO	n/a
BRS Stop	STOP (then Y/N)	n/a
Test Voice Alert	TALK	n/a
Login Maintenance	LOGM	n/a
Grant Maintenance Mode	GM	n/a
Deny Maintenance Mode	DM	n/a
Select Tape Drive	TAPE (n)	N = 1 - 2
Start Recording	REC	n/a
Stop Recording	STPT	n/a
Pause Playback	PPB	n/a
Resume Playback	RPB	n/a
Rewind Tape	REW	n/a
Advance to End of Written Tape	ADV	n/a
Search For Time Tag	SRCH_(ddmmmyy)/(hhmm)	n/a
Next File Search	NFS	n/a
Previous File Search	PFS	n/a
Beginning of File Search	BFS	n/a
Select Print Options Menu	POM	n/a
Print Data	PRINT	n/a
Operational Backup	OP (n)	N = 15 - 32

Maintenance Commands

Save Controller Setup	CSAV_(Name)	n/a
Delete Controller Setup	DCS_(Name)	n/a
Display Stretch	AR (n)	N = 1 - 4
Track Filter Select	(RW#) B	n/a
Center Around Cursor	OC	n/a
Center Around Antenna	OA	n/a
Set Display Size	ZR (n)	N = 2 - 32 Even values only
Logoff Maintenance	LOGOM	n/a